



SERVICES

INTERNAL TELEPHONES

**P.A.X.
INTERNAL
TELEPHONES—**

**SECRETARIAL
FACILITY**



Secretary's Special Telephone



**Executive's Special Telephone
(K. 151)**

This telephone for the use of personal secretaries has been specifically designed to operate in conjunction with an Executive's internal telephone, which may be either a TR Paxmaster or a special telephone for "secretarial working" (see illustration left).

Basically it is a standard TR P.A.X. telephone incorporating components to G.P.O. specifications, of British manufacture throughout, and is attractively styled in two-tone grey moulded plastic to harmonize with the decor in modern offices.

The switching operations involved are readily effected by means of the press buttons which are clearly labelled, and the lamp fitted by the dial provides visual signalling.

For details see overleaf . . .



Head Office: 197 KNIGHTSBRIDGE, LONDON, S.W.7. KENsington 1471



SECRETARY'S SPECIAL TELEPHONE

(K. 152)

Overall dimensions

Width 5½"

Width (over handset) 9¼"

Depth 8½"

Height 5"

Facilities

- 1** All incoming calls to the Executive's telephone are signalled visually on both instruments and, in addition, audibly on either one as desired by the Executive, for which purpose his instrument is provided with a transfer key or button. Under all conditions any call to the Executive's instrument can be answered by him or on the Secretary's instrument.
- 2** Secret conversation between Executive and Secretary is provided for by a private line independent of the switchboard and the Secretary can refer to the Executive while holding a call without being overheard by the caller. Alternatively, the Executive can call the Secretary into a conversation as a third party.
- 3** The Secretary's instrument has its own P.A.X. line on which calls may be made and received in the same way as on any normal telephone. However, in the event of the Secretary being engaged on the Executive's P.A.X. line or private line, incoming calls on the Secretary's P.A.X. line can be rejected by operating the "busy" button which causes the "busy" tone to be received by the caller.



T 406/1